

# Linortek Netbell®- KB-M2-C Network Break Buzzer Clock System

**Self-Contained, Easy-To-Use, Remote Access, Scheduling Buzzer Over the Network, No Additional Software or Designated Computer Required**

## Applications

Provide remote access to control timed alert system for:

- Factories
- Warehouses
- Any other places need a timed alert system for breaks, shift changes or general alarms

## The Key Features

- Network enabled, access the Netbell from any computer on the network
- All-in-one system, no additional software or designated computer required
- Import/export schedules from existing data in text format
- Flexible and accurate control of when the bells ring (HH:MM:SS,MM/DD/YYYY, SUNDAY- SATURDAY)
- Built-in real time clock sync its time from NTP server every 30 minutes (user changeable)
- Built-in rechargeable battery protected auxiliary real time clock
- Use as either a network device or a standalone device
- Designed, developed and built in the USA with global materials



Linortek Netbell® is an ease-of-use, network enabled, custom developed device for schools, factories, warehouses and other organizations to build a fully automated web-based timed alert system for signaling shift changes, general alarm, and breaks in areas of high ambient noise levels. The system is built on a TCP/IP platform with a built in web server, which allows users to access, control, and schedule the Bells or buzzers accurately and effectively using an Internet connection from anywhere over the network, with no additional software or designated computer required.

The Netbell-KB-M2-C is a network enabled, all-in-one break buzzer system with 4" digital clock that can synchronize its time from the Netbell NTP Server, so that you will get a consistent time displayed and synchronized with your buzzer system. The Netbell-KB-M2 features a 4 inch high quality buzzer that can cover up to 25,000 Sqft industrial working areas (110dBA @1M, volume adjustable), and a completely wired web-based bell controller installed within a NEMA-rated box. There are two additional outputs to connect two external buzzers (not included) if needed. With a push switch connecting to the digital input, you can ring the buzzer manually for emergency.

The digital clock comes with 3M cable that you can plug it to the Netbell-KB clock output directly, no configuration required and it will synchronize its time from the Netbell automatically. With the large, bright 4 inch high digits, the clocks are easily visible up to 250ft.

# Netbell® Technical Specifications

## Netbell-KB All-In-One Extra Loud Buzzer Clock System

### General Information

Model	<a href="#">Netbell-KB-C</a>	<a href="#">Netbell-KB-M2-C</a>	<a href="#">Netbell-KB-E1-C</a>	<a href="#">Netbell-KB-E2M-C</a>
Part#	01-910-00072	01-910-00065	01-910-00085	01-910-00086

### Technical Specification

Bell Scheduling Software	Built- In (All software located on built-in web server.)			
Event Schedules	Up to 500 Web-Based Event Schedules (Add schedules from web browser)			
Bell Ringing Duration	User Programmable for Each Schedule			
4" LED Digital Clock	1			
Built-In Buzzer (4", 110dBA @ 1m, volume adjustable)	1			
External Buzzer Output (s)	1	2	1	2
External Buzzer (s)	0	0	1	2
Coverage (SQ FT)	25,000	25,000	50,000	75,000
Manual Bell Control (For emergency)	Yes			
Push Switch	Optional			
Enclosure	ABS, IP66 /150mm x 150mm x 90mm			
Accessories	Power Cable/RJ45 Cable/Mounting Brackets/Volume Adjustment Kit			
Power Input	24VAC (Power supply included)			
Voltage Sensor	On Board			
Temperature Sensor	On Board			
Rechargeable Battery	On Board (For offline time & settings keeping backup up to 7 days)			
Working Temperature	From 0 to +60 Celsius			
Supported Protocols	HTTP/ SMTP/SNTP			

