



# Philips EasySense / SpaceWise Compatible Wireless Switch

ILLUMRA ZBT-S1AWH and ZBT-S2AWH switches are for use with the Philips EVO200, EvoKit, Spacewise DT, SNS120, SNH200, SNS200, SNS210 MC.

ILLUMRA™ ZigBee Switches offer a familiar and convenient interface for controlling Signify EasySense and SpaceWise products. The switches do not require wires or batteries, they contain a micro-generator powered ZigBee transmitter to send a wireless signal. The signal transmits through walls or around corners.

Philips EasySense configuration software is used to configure the behavior and allows the rocker to be configured for On/Off function and also works as press and hold dim to adjust brightness up and down. If using a Dual Rocker switch, the left rocker would perform the on/off and dim functions, and the right side can be configured for Scene Recall - the top and bottom buttons each dim to a level that is adjustable in the configuration software.

## Self Powered - No Batteries! No Wires!



## Compatible Philips EasySense and SpaceWise products

ILLUMRA ZBT-S1AWH and ZBT-S2AWH switches are for use with the Philips EVO200, EvoKit, Spacewise DT, SNS120, SNH200, SNS200, SNS210 MC.

### Available Colors:



White



Light Almond



Ivory



Gray



Brown



Black

Part Number	ZBT-S1A(x)	ZBT-S2A(x)
Range	30ft (10m)	
Frequency	ZigBee Channels 11-26 (2.4Ghz)	
Power	Self-generated when switch is pressed	
Buttons	2 Buttons	4 Buttons
Dimensions	2.75 (W) x 4.5 (H) x 0.62 (D) inches 6.98 (W) x 11.43 (H) x 1.57 (D) cm	
Ordering Codes	ZBT-S1AWH (White) ZBT-S1ABR (Brown) ZBT-S1ALA (Light Almond) ZBT-S1ABK (Black) ZBT-S1AIV (Ivory) ZBT-S1AGY (Gray)	ZBT-S2AWH (White) ZBT-S2ABR (Brown) ZBT-S2ALA (Light Almond) ZBT-S2ABK (Black) ZBT-S2AIV (Ivory) ZBT-S2AGY (Gray)

115 S State St, Suite B  
Lindon, UT 84042

T: (801) 349-1200  
F: (801) 614-7100  
Sales@ILLUMRA.com