



ANATECH ELECTRONICS INC
RF & Microwave Filters & Products

1870-1890 MHz Cavity Bandpass Filter

Part Number: AB1880B1221



Frequency Range	1870~1890MHz
Insertion Loss	<2.0dB
Return Loss	> 14dB
Rejection	>50dBc@1840MHz >50dBc@1920MHz
Size Tolerance	As below (+/- 0.3mm)

<u>Mechanical</u>	
Mounting Method:	Threaded Mounting Holes
Connector Type:	SMA (F)
Dimensions:	104.7x 25.4 x 38.1 mm

<u>Environmental</u>	
Operating Temperature:	-40 to +70 deg.C
Storage Temperature:	-50 to +90 deg.C

Outline Drawing:

