


# ProtoBox-1593L Kit (PCB+Box)



*A Hammond 1593L handheld plastic enclosure packaged with a matching BPS ProtoBoard 2-hole per strip PCB.*



**BusBoard Prototype Systems** - Built for designers

[www.BusBoard.com](http://www.BusBoard.com) [sales@busboard.com](mailto:sales@busboard.com)

BPS-MAR-(KIT-1593L)-001 Rev 4.00

*A prototyping board designed for the Hammond 1593L handheld enclosure.*

## Features

*ProtoBoard* saves time! The PCB is designed specifically for the Hammond 1593L box. No cutting is required. The mounting holes are present in the right spots.

The convenient 2-hole ProtoBoard pattern provides an easy way to connect parts while maximizing usable board area.



**Lead free** etched copper PCB with an anti-tarnish coating for easy soldering.

## PCB Specifications

- High-quality FR4 glass epoxy board.
- Four 0.125" (1/8") mounting holes.
- Four 4-40 PCB mounting screws provided.
- Single sided, 1oz/ft<sup>2</sup> copper PCB
- 0.042" holes drilled on 0.1" centers
- PCB Size 3.3 x 2.3 in. (83 x 58mm)

**Order Part# PR1593L (for PCB only)**

## Board Layout (actual size)




**PR1593L Prototyping Board shown with the Hammond 1593LBK box (box not included).**


**To purchase the PCB + Box together,  
order BPS part# KIT-1593L-BK**




### Top View of Assembly




### SECTION A-A (Side View Inside Assembly)




## Hand Held Instrument (1593L)



### End View of Assembly





### SECTION B-B (Inside of Bottom Cover)



### Maximum P.C. Board Size

### Front/Rear Panel (Dashed Line Indicates Viewing Area)



Enclosures can be Factory Modified ( Milling, Drilling, Printing etc. )  
 Solid models of this enclosure available in STEP or IGES.  
 Contact Factory [mjm@hammondmfg.com](mailto:mjm@hammondmfg.com)

NOTE	
Enclosure molded from GP ABS (UL94-HB) plastic.	
Purchased assembly includes top and bottom cover, front and rear plastic panels (2 types - flat and contoured) and 4 cover screws.	

PART NUMBERS	
<b>1593L Enclosure</b>	
Black Enclosure	1593LBK
Grey Enclosure	1593LGY
ACCESSORIES	
Cover Screws (Pkg 100)	1593QS100 (Silver)
#4 x 3/4" self-tapping oval head (19.1mm)	1593QS100BK (Black)
P.C. Board Screws	1593ATS50 (Pkg 50)
#4 x 1/4" self-tapping (6.4mm)	1593ATS100 (Pkg 100)
Belt or Pocket Clip	1599CLIP (Black)
	1599CLIPGY (Grey)
Infrared Panels (Pkg 10)	1593DIR10

**HAMMOND MANUFACTURING™**  
**1593L**  
[www.hammondmfg.com](http://www.hammondmfg.com)